

The Vista S3

Control Console.

All the control surface you need.



The Jands Vista S3 is a compact version of the Vista that puts all the revolutionary features of the full-scale console into a desk you can fit under your arm.

The S3 gives you all the features that make the Vista such a great live desk: big, clear LCDs, fader banks you can split or combine and a set of user configurable shortcut buttons. With 20 playbacks (10 with faders), four DMX outputs, timecode † input and three encoder wheels, you'll have all the control you need.

Of course, the S3 also features the Vista's incredible generic fixture model, so no matter what rig you've programmed your show for, the S3 adapts automatically if you have to run the same show with a different rig, without the need for re-programming.

Designed to be used with your desktop or laptop, the S3 is a Vista without the computer hardware components: we provide the software and the control surface, you provide the computer. Install the software, connect your PC to the S3 with a USB cable, and you've got a fully-operational Vista console.



Feature List

Main Controls

- 6 user configurable function buttons
- Blue, Green, Yellow, Red modifier buttons
- Power button
- Grand Master (rotary) fader and DBO button

Playback Controls

- 20 Playbacks, 10 with faders and flash buttons, 10 without
- Playbacks feature; Blue / White LCD, Select and Go buttons
- Split mode allows control of up to 50 Cuelists
- Playbacks can be configured for control of Groups, Presets and more
- Page Up / Down buttons

Super Playback Controls

- Playback with 2 faders and buttons
- Go, Pause, Back, Skip Forward, Skip Reverse, Skip to Start, Skip to End buttons
- Utilises LCD and Encoder wheels for display and real time control of playback and other advanced functions.

Programming Controls

- 3 Encoder Wheels with associated Blue / White LCD
- Next / Previous buttons
- 12 context sensitive function buttons

DMX Output

- DMX output channels determined by dongle – sold separately
- 128, 256, 512, 1024, 2048 or 8192 channel versions available
- Specify requirements at time of purchase
- Upgrades available

Input and Output Connections

- 4 DMX outputs (* Actual DMX output channels determined by dongle. Software pack, including dongle, must be purchased separately.)
- 5 USB2 connectors (4 A type, 1 B type)
- Linear Time code input †
- MIDI in/thru/out †
- Desk lamp outlet

Specifications

- Processor : 60MHz Philips ARM7
- SRAM : 128 Kbytes
- Dimensions (l w d) : 642mm x 530mm x 140mm
- Weight : 16kg Net 21kg Shipping

System Requirements for the Vista application:

- Intel i3 or better processor
- Windows 7 Professional 32 or 64 bit
- 2.0GB of RAM (4.0GB recommended)
- 500MB available hard disk space

† Not implemented in V2.0



www.jandsvista.com

